

TRANSISTOR NUMBER	PM OAL T	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
25C1168	NS	T066	L43	300V		5V	150MA	150C	12WC	20M		25MN	50MA	AME	TOS	BLY50A	2N3739	1
25C1170	NS	T03	L05	1K2V	500V	5V	3A5	150C	50WC	2M		10MN	1A	TLE	TOS	BU208		2
25C1170B	NS	T03	L05	1K5V	500V	5V	3A5	150C	50WC	1M5	190P	10MN	1A	TLE	TOS	BU308		1
25C1171	NS	T03	L05	1K1V	700V	5V	1A	150C	50WC	800K		30MN	150MA	TLE	TOS	BU205		1
25C1172	NS	T03	L05		600V	5V	5A	150C	50WC	2M		10MN	2A	TLE	TOS			0
25C1172A	NS	T03	L05	1K5V	600V	5V	5A	150C	50WC	1M	300P	10MN	2A	TLE	TOS	BU225		2
25C1172B	NS	T03	L05	1K5V	600V	5V	7A	150C	50WC	1M5	300P	10MN	2A	TLE	TOS	BU308		2
25C1173	NS	TOP66	L32	45V	30V	5V	3A	150C	25WC	1M		40/240	500MA	AHG	TOS	BD589	2N6123	0
25C1173/G	NS	TOP66	L32	45V	30V	5V	3A	150C	25WC	1M		200MN	500MA	AHG	TOS	BD589	2N6123	0
25C1173/R	NS	TOP66	L32	45V	30V	5V	3A	150C	25WC	1M		40/80	500MA	AHG	TOS	BD589	2N6123	0
25C1173/Y	NS	TOP66	L32	45V	30V	5V	3A	150C	25WC	1M		120MN	500MA	AHG	TOS	BD589	2N6123	0
25C1173/O	NS	TOP66	L32	45V	30V	5V	3A	150C	25WC	1M		70/140	500MA	AHG	TOS	BD589	2N6123	0
25C1174	NS	T03	L05	1K2V	700V	6V	3A5	150C	50WC	2M		4MN	3A5	HIJ	BU208		1	
25C1175	NS	T092	L21	50V	45V		220MA	125C	280MWF	80M		30MN	5MA	RMG	BCW36	2N3905	1	
25C1176	NS	X28	L65	40V		4V5	1A	175C	15WC	300M		20MN	100MA	VHP	MIT			1
25C1177	NS	X28	L65	40V		4V5	2A5	175C	25WC	300M		20MN	100MA	VHP	MIT			1
25C1178	NS	X27	L64	40V		5V	5A	175C	35WC	90M	10MN	200MA		RHP	MIT			2
25C1178A	NS	X56E	X56	40V	18V	4V5	5A	175C	35WC	225M	160P	10/180	200MA	VHP	MIT	BLW25		1
25C1180	NS	T072	L06	30V	25V	4V	30MA	170C	150MWF			40MN	10MA	VLG	SAN			2
25C1184	NS	T03	L05	900V		5V	1A	150C	50WC			30MN	200MA	AME		BU206		1
25C1185	NS	T03	L05	300V		5V	1A5	150C	50WC			40MN	400MA	AME		BU113		1
25C1187	NS	T092	L21	40V		4V	25MA	125C	250MWF	300M		40MN	3MA	VLA		BFX73	2N918	1
25C1188	NS	T092	L21	40V		4V	30MA	125C	250MWF	425M		40MN	10MA	VLA		BFX73	2N918	1
25C1189	NS	T092	L21	40V		4V	30MA	125C	250MWF	425M		40MN	10MA	VLA		BFX73	2N918	1
25C1190	NS	X55E	X55	36V	18V	4V	5A	175C	30WC	300M	34P	10MN	400MA	VHP	MAT	BLY93	2N4127	2
25C1191	NS	X78E	X78	36V	18V	4V	7A	175C	45WC	200M	100P	10MN	800MA	VHP	MAT			2
25C1192	NS	X78E	X78	36V	18V	4V	10A	175C	60WC	175M	200P	10MN	1A	VHP	MAT			2
25C1193	NS	X38		20V	15V	3V	30MA	175C	200MWF	2G		20MN	10MA	SLA	TOS			1
25C1195	NS	T03	L05	200V	180V	6V	2A5	200C	90WC	5M		40MN	1A	RHE	TOS	BDY26	2N5157	1
25C1196A	NS	X55E	X55	45V		3V5	1A	175C	10WC	500M		20MN	200MA	UHP	TOS			2
25C1197A	NS	X55E	X55	45V		3V5	2A	175C	20WC	500M		20MN	500MA	UHP	TOS			2
25C1198	NS	X55E	X55	45V	35V	4V	3A5	175C	30WC	400M		20/120	1A	UHP	TOS			2
25C1199	NS	T039	L04	50V	40V	5V	300MA	180C	650MWF	600M		30MN	10MA	UMG	TOS	BFW47	2N3137	0
25C1200	NS			40V	20V	3V5	1A5	175C	10WC	800M		20MN	500MA	UHP	TOS			0
25C1204	NS	X21	L41	30V	30V	5V	100MA	125C	310MWF	100M		100MN	2MA	ALG	HIJ	BC349C	2N3904	1
25C1205	NS	X21	L41	30V	30V	5V	100MA	125C	310MWF	100M		35MN	2MA	ALG	HIJ	BC349C	2N3904	1
25C1206	NS	X21	L41	45V	40V	5V	2A	125C	310MWF	100M		35MN	500MA	AMG	MIT	BFT29		1
25C1206B	NS	X54C	X54	45V	4V	2A	2A	175C	30WC	750M	24P	10/180	100MA	UMP	MIT	BLX69		2
25C1207	NS	X28	L65	45V	4V	3A	175C	40WC	300M			20MN	300MA	VHP	MIT			1
25C1208	NS	X28	L65	36V		5V	10A	175C	60WC	90M		20MN	500MA	RHP	MIT			1
25C1208A	NS	X55	X55	36V	18V	5V	10A	175C	60WC	225M		10/180	500MA	VHP	MIT	BLY94		2
25C1209	NS	T092	L21	25V	20V	4V	500MA	125C	500MWF	75M		35MN	500MA	AMG	MIT			1
25C1210	NS	T092	L21	45V	40V	4V	500MA	125C	500MWF	75M		35MN	150MA	AMG	MIT			1
25C1211	NS	T092	L21	65V	60V	4V	500MA	125C	500MWF	75M		35MN	500MA	AMG	MIT			1
25C1212	NS	T0126	L31	60V		4V	1A	125C	750MWF			35/320	50MA	AMG	HIJ	BD169	2N4923	0
25C1212A	NS	T0126	L31	90V		4V	1A	125C	750MWF			35/320	50MA	AMH	HIJ	BD169	2N4923	0
25C1213	NS	X21	L78	35V	35V	5V	500MA	125C	400MWF	100M		40MN	10MA	AMG	HIJ			1
25C1213A	NS	X19	L45	50V	50V	4V	500MA	125C	400MWF	60M	14P	40MN	10MA	AMG	HIJ	BSW66	2N4001	2
25C1214	NS	X21	L78	50V	50V	5V	500MA	125C	600MWF	100M		40MN	10MA	AMH	HIJ			1
25C1215	NS	T092	L21	30V	20V	3V	50MA	125C	200MWF	600M	2R	25MN	2MA	ULA	MAT			2
25C1216	NS	T018	L01	40V	20V		200MA	175C	300MWF	250M	50P	60/300	10MA	VLS	NIP			2
25C1217	NS	T05	L04	150V	130V	5V	500MA	175C	1WF	125M		50MN	100MA	RME	NIP			1
25C1218	NS	T05	L04	90V	80V	5V	500MA	175C	1WF	185M		50MN	100MA	RMH	NIP			1
25C1220	NS	T092	L21	50V	30V	5V	500MA	125C	200MWF		24P	160TP	100MA	AMG	FUJ	BCW36	2N4953	2
25C1222	NS	T092	L21	50V	30V	5V	30MA	125C	250MWF	50M		150MN	500UA	ALN	NIP	BC184L	2N5210	2
25C1222E	NS	T092	L21	60V	50V	5V	100MA	125C	250MWF	50M	7P	350MN	500UA	ALN	NIP	BC184L	2N5089	2
25C1222F	NS	T092	L21	60V	50V	5V	100MA	125C	250MWF	50M	7P	225MN	500UA	ALN	NIP	BC184L	2N5089	2
25C1222W	NS	T092	L21	60V	50V	5V	100MA	125C	250MWF	50M	7P	500MN	500UA	ALN	NIP	BC184L	2N5089	2
25C1223	NS	T05	L04	30V	16V	4V	500MA	175C	800MWF	100M		20MN	10MA	RMG	MIT	BSW54	2N2219A	1
25C1226	NS	X17	L32	40V	20V	5V	3A	150C	10WC	75M		30/220	1A	RHG	MAT	BD239		2
25C1226A	NS	X17	L32	50V	40V	5V	3A	150C	10WC	75M		30/220	1A	RHG	MAT	BD241C		2
25C1228	NS	T03	L05	500V	400V	5V	10A	175C	100WC			15TP	5A	AHE	FUJ	BUX14	2N6560	2
25C1229	NS	T03	L05	250V	250V	5V	10A	175C	100WC	13M		50TP	5A	RHE	FUJ	BUX12	2N6561	2
25C1230	NS	T03	L05	450V	400V	5V	10A	175C	100WC	7M		15TP	5A	RHE	FUJ	BUX14	2N6560	2
25C1231	NS	T018	L01	20V	14V	4V	200MA	175C	300MWF	400M		60TP	10MA	SLS	FUJ			2
25C1235	NS	T066	L43	300V	300V	4V	100MA	150C	10WC	30M		30/160	50MA	RLE	SAN	BUX67B	2N3739	2
25C1236	NS	X38	X38	20V	15V	3V	30MA	175C	200MWF	3G		20MN	10MA	SLG	TOS			1
25C1238	NS	X28	L65	35V	25V	4V	150MA	175C	5WC	400M		20MN	15MA	ULP	MIT			1
25C1239	NS	T037	L47	80V	60V	4V5	4A	175C	13WC	10M		10MN	100MA	RHP	MIT			1
25C1240	NS	T092	L21	40V		3V	50MA	125C	350MWF	300M		30MN	10MA	VLG				1
25C1241A	NS	X55E	X55	35V	18V	3V5	2A	175C	20WC	75M		10MN	1A	VHP	TOS			2
25C1242A	NS	X55E	X55	35V	18V	3V5	4A5	175C	20WC	75M		10/200	1A5	VHP	TOS			2
25C1243	NS	X17	L56	25V	20V	5V	1A5	150C	10WC			35MN	500MA	MIT		BD237	2N4923	1
25C1246A	NS	T092	L21	30V	20V	5V	500MA	175C	500MWF	30M	24P	160TP	100MA	AMG	FUJ	BCW36	2N4953	2
25C1247A	NS	T092	L21	50V	30V	5V	500MA	175C	500MWF	30M	24P	160TP	100MA	AMG	FUJ	BCW36	2N4953	2